



NOD UN

ZIGBEE DOOR AND WINDOW OPEN DETECTOR

Zigbee Door and Window Open Detector

REF: NO-SDO-4-1-01 EAN: 3700313925973 EXISTE EM: BRANCO

DESCRIÇÃO:

The Zigbee Door and Window Open Detector allows you to know in real time the open/closed status of a window or door. It reports the information to an actuator or home automation hub to help achieve energy savings.

PONTOS FORTES:

NO BATTERY

The detector is powered by light (optional battery).

• QUICK INSTALLATION

Wireless, mounts with double-sided adhesive or screws.

• AUTOMATIC REPORTING

The sensor automatically sends a report of its different states, every hour (default) or based on your needs (configurable).

• OVER-THE-AIR (OTA) UPDATE

The sensor is quick to update thanks to the OTA function. Updates can be performed via a compatible home automation hub.

CARACTERÍSTICAS:

Power

Energy harvesting via photovoltaic cell.

Battery (optional)

CR2032 (3 years).



• Operating temperature

-5 / +45°C.

• Frequency band used

Zigbee 2.4GHz.

• Maximum radio power

7dBm/5mW.

• Radio protocol

Zigbee 3.0.

• Zigbee profile

0x0402 : IAS Zone.

• Range

30m indoors.

• Dimensions

34mm (w) x 85mm (L) x 15mm (h).

• Protection rating

IP20.

• Weight

30g.

• Warranty

2 years.

• Compatibility

The Zigbee door and window open detector works only with a compatible Zigbee home automation hub (remote monitoring and surveillance).